





Standard Reducing Couplings

11 Gauge Reducing Couplings Available

STANDARD REDUCING COUPLINGS

PART NO.	SIZE	A(OD)	GAUGE	C	D	E(ID)	GAUGE	K
RC-212	2-1/8" x 2"	2-1/8"	16	4"	1-1/8"	2"	16	2"
RC-254	2-1/2" x 2-1/8"	2-1/2"	16	4-1/2"	1-1/4"	2-1/8"	16	1-1/2"
RC-3041	3" x 2-1/8"	3"	16	8-3/4"	1-1/4"	2-1/8"	16	2"
RC-304	3" x 2-1/2"	3"	16	5"	1-1/4"	2-1/2"	16	1-1/2"
RC-3541	3-1/2" x 2-1/8"	3-1/2"	16	11"	1-1/4"	2-1/8"	16	2"
RC-3542	3-1/2" x 2-1/2"	3-1/2"	16	9-1/4"	1-1/4"	2-1/2"	16	2-7/8"
RC-354	3-1/2" x 3"	3-1/2"	16	5-1/2"	1-1/4"	3"	16	1-1/2"
RC-4041	4" x 2-1/8"	4"	16	13-1/2"	1-1/4"	2-1/8"	16	2"
RC-4042	4" x 2-1/2"	4"	16	10-1/2"	1-1/4"	2-1/2"	16	2"
RC-4043	4" x 3"	4"	16	9-1/4"	1-1/4"	3"	16	2"
RC-404	4" x 3-1/2"	4"	16	6"	1-1/4"	3-1/2"	16	1-1/2"
RC-5041	5" x 2-1/8"	5"	14	19-1/4"	1-1/4"	2-1/8"	16	2-3/4"
RC-5042	5" x 2-1/2"	5"	14	17-1/2"	1-1/4"	2-1/2"	16	2-3/4"
RC-5043	5" x 3"	5"	14	15"	1-1/4"	3"	16	2-3/4"
RC-5044	5" x 3-1/2"	5"	14	12-1/2"	1-1/4"	3-1/2"	16	2-3/4"
RC-504	5" x 4"	5"	16	8"	1-1/4"	4"	16	1-3/4"
RC-6041	6" x 2-1/8"	6"	14	24-3/4"	1-1/4"	2-1/8"	16	3-1/4"
RC-6042	6" x 2-1/2"	6"	14	23"	1-1/4"	2-1/2"	16	3-1/4"
RC-6043	6" x 3"	6"	14	20-1/2"	1-1/4"	3"	16	3-1/4"
RC-6044	6" x 3-1/2"	6"	14	18"	1-1/4"	3-1/2"	16	3-1/4"
RC-6045	6" x 4"	6"	14	15-3/4"	1-1/4"	4"	16	3-1/4"
RC-604	6" x 5"	6"	14	10"	1-1/2"	5"	14	1-3/4"
RC-8044	8" x 4"	8"	14	26-1/4"	1-1/4"	4"	16	4-1/4"
RC-8045	8" x 5"	8"	14	21-7/8"	1-1/2"	5"	14	4-1/4"
RC-804	8" x 6"	8"	14	17-1/2"	1-1/2"	6"	14	4-1/4"
RC-10046	10" x 6"	10"	12	28-1/2"	1-1/2"	6"	14	5-1/4"
RC-1004	10" x 8"	10"	12	18-1/4"	2-1/2"	8" OD	14	5-1/4"
RC-12048	12" x 8"	12"	12	29-1/4"	2-1/2"	8" OD	14	6-1/4"
RC-1204	12" x 10"	12"	12	19-3/4"	3"	10" OD	12	6-1/4"
RC-1404	14" x 10"	14"	12	30"	3"	10" OD	12	7-1/4"
RC-1405	14" x 12"	14"	12	20"	4"	12" OD	12	7-1/4"



OD = Outside Diameter
ID = Inside Diameter

All reference dimensions are nominal.
Catalog Part Variations Available Upon Request.

Expanded Ends standard through 6" size (on small end of reducer).

Straight Ends available on all sizes by request.